

J21 (group 0)

- 1 - RS422 out - this output has not yet been implemented in firmware
- 2 - RS422 out (MBARI DVL trigger)
- 3 - local ground group 0 (V_0C)
- 4 - TX with jumper change (R1)to RS232 – Not supported in firmware
- 5 - RX with jumper change (R87)to RS232 - Needs firmware update to 0x_ _ -
- 6 - local ground group 0 (V_0C)
- 7 - RS422 INPUT - Currently is not supported in the firmware
- 8 - RS422 INPUT - Currently is not supported in the firmware

J23 (group 2)

- 1 - TTL or RS232 OUTPUT (jumpper configured) - Currently is not supported in the firmware
- 2 - fixed Trigger out TTL
- 3 - local ground group 2 (V_2C)
- 4 - Variable Trigger out TTL
- 5 - TTL or RS232 INPUT (jumpper configured) - Currently is not supported in the firmware
- 6 - local ground group 2 (V_2C)
- 7 - trigger in "TTL"
- 8 - INPUT "TTL" - Currently is not supported in the firmware

J24 (group 3)

- 1 - TTL or RS232 OUTPUT (jumpper configured) - Currently is not supported in the firmware
- 2 - TTL OUTPUT - Currently is not supported in the firmware
- 3 - local ground group 3 (V_3C)
- 4 - TTL OUTPUT - Currently is not supported in the firmware
- 5 - TTL or RS232 INPUT (jumpper configured) - Currently is not supported in the firmware
- 6 - local ground group 3 (V_3C)
- 7 - "TTL" input - Currently is not supported in the firmware
- 8 - PPS