

PIC32MX150F128B



Peripheral Module Disable Configuration:

PMDL1WAY = OFF	Allow multiple reconfigurations
PMDL1WAY = ON	Allow only one reconfiguration

Peripheral Pin Select Configuration:

IOL1WAY = OFF	Allow multiple reconfigurations
IOL1WAY = ON	Allow only one reconfiguration

USB USID Selection:

FUSBIDIO = OFF	Controlled by Port Function
FUSBIDIO = ON	Controlled by the USB Module

USB VBUS ON Selection:

FVBUSONIO = OFF	Controlled by Port Function
FVBUSONIO = ON	Controlled by USB Module

PLL Input Divider:

FPLLIDIV = DIV_1	1x Divider
FPLLIDIV = DIV_2	2x Divider
FPLLIDIV = DIV_3	3x Divider
FPLLIDIV = DIV_4	4x Divider
FPLLIDIV = DIV_5	5x Divider
FPLLIDIV = DIV_6	6x Divider
FPLLIDIV = DIV_10	10x Divider
FPLLIDIV = DIV_12	12x Divider

PLL Multiplier:

FPLLMUL = MUL_15	15x Multiplier
FPLLMUL = MUL_16	16x Multiplier
FPLLMUL = MUL_17	17x Multiplier
FPLLMUL = MUL_18	18x Multiplier
FPLLMUL = MUL_19	19x Multiplier
FPLLMUL = MUL_20	20x Multiplier
FPLLMUL = MUL_21	21x Multiplier
FPLLMUL = MUL_24	24x Multiplier

System PLL Output Clock Divider:

FPLLODIV = DIV_1	PLL Divide by 1
FPLLODIV = DIV_2	PLL Divide by 2
FPLLODIV = DIV_4	PLL Divide by 4
FPLLODIV = DIV_8	PLL Divide by 8
FPLLODIV = DIV_16	PLL Divide by 16
FPLLODIV = DIV_32	PLL Divide by 32
FPLLODIV = DIV_64	PLL Divide by 64
FPLLODIV = DIV_256	PLL Divide by 256

Oscillator Selection Bits:

FNOSC = FRC	Fast RC Osc (FRC)
FNOSC = FRCPLL	Fast RC Osc with PLL
FNOSC = PRI	Primary Osc (XT,HS,EC)
FNOSC = PRIPLL	Primary Osc w/PLL (XT+,HS+,EC+PLL)
FNOSC = SOSC	Low Power Secondary Osc (SOSC)
FNOSC = LPRC	Low Power RC Osc (LPRC)
FNOSC = FRCDIV16	Fast RC Osc w/Div-by-16 (FRC/16)
FNOSC = FRCDIV	Fast RC Osc w/Div-by-N (FRCDIV)

Secondary Oscillator Enable:

FSOSCEN = OFF	Disabled
FSOSCEN = ON	Enabled

Internal/External Switch Over:

IESO = OFF	Disabled
IESO = ON	Enabled

Primary Oscillator Configuration:

POSCMOD = EC	External clock mode
POSCMOD = XT	XT osc mode
POSCMOD = HS	HS osc mode
POSCMOD = OFF	Primary osc disabled

CLKO Output Signal Active on the OSCO Pin:

OSCIOFNC = ON	Enabled
OSCIOFNC = OFF	Disabled

Peripheral Clock Divisor:

FPBDIV = DIV_1	Pb_Clk is Sys_Clk/1
FPBDIV = DIV_2	Pb_Clk is Sys_Clk/2
FPBDIV = DIV_4	Pb_Clk is Sys_Clk/4
FPBDIV = DIV_8	Pb_Clk is Sys_Clk/8

Clock Switching and Monitor Selection:

FCKSM = CSECME	Clock Switch Enable, FSCM Enabled
FCKSM = CSECMD	Clock Switch Enable, FSCM Disabled
FCKSM = CSDCMD	Clock Switch Disable, FSCM Disabled

Watchdog Timer Postscaler:

WDTPS = PS1	1:1
WDTPS = PS2	1:2
WDTPS = PS4	1:4
WDTPS = PS8	1:8
WDTPS = PS16	1:16
WDTPS = PS32	1:32
WDTPS = PS64	1:64
WDTPS = PS128	1:128
WDTPS = PS256	1:256
WDTPS = PS512	1:512
WDTPS = PS1024	1:1024
WDTPS = PS2048	1:2048
WDTPS = PS4096	1:4096
WDTPS = PS8192	1:8192
WDTPS = PS16384	1:16384
WDTPS = PS32768	1:32768
WDTPS = PS65536	1:65536
WDTPS = PS131072	1:131072
WDTPS = PS262144	1:262144
WDTPS = PS524288	1:524288
WDTPS = PS1048576	1:1048576

Watchdog Timer Window Enable:

WINDIS = ON	Watchdog Timer is in Window Mode
WINDIS = OFF	Watchdog Timer is in Non-Window Mode

Watchdog Timer Enable:

FWDTEN = OFF	WDT Disabled (SWDTEN Bit Controls)
FWDTEN = ON	WDT Enabled

Watchdog Timer Window Size:

FWDTWINSZ = WINSZ_75	Window Size is 75%
FWDTWINSZ = WINSZ_50	Window Size is 50%
FWDTWINSZ = WINSZ_37	Window Size is 37.5%
FWDTWINSZ = WINSZ_25	Window Size is 25%

Background Debugger Enable:

DEBUG = ON	Debugger is Enabled
DEBUG = OFF	Debugger is Disabled

JTAG Enable:

JTAGEN = OFF	JTAG Disabled
JTAGEN = ON	JTAG Port Enabled

ICE/ICD Comm Channel Select:

ICESEL = RESERVED	Reserved
ICESEL = ICS_PGx3	Communicate on PGEC3/PGED3
ICESEL = ICS_PGx2	Communicate on PGEC2/PGED2
ICESEL = ICS_PGx1	Communicate on PGEC1/PGED1

Program Flash Write Protect:

PWP = PWP32K	First 32K
PWP = PWP31K	First 31K
PWP = PWP30K	First 30K
PWP = PWP29K	First 29K
PWP = PWP28K	First 28K
PWP = PWP27K	First 27K
PWP = PWP26K	First 26K
PWP = PWP25K	First 25K
PWP = PWP24K	First 24K
PWP = PWP23K	First 23K
PWP = PWP22K	First 22K
PWP = PWP21K	First 21K

PWP = PWP20K	First 20K
PWP = PWP19K	First 19K
PWP = PWP18K	First 18K
PWP = PWP17K	First 17K
PWP = PWP16K	First 16K
PWP = PWP15K	First 15K
PWP = PWP14K	First 14K
PWP = PWP13K	First 13K
PWP = PWP12K	First 12K
PWP = PWP11K	First 11K
PWP = PWP10K	First 10K
PWP = PWP9K	First 9K
PWP = PWP8K	First 8K
PWP = PWP7K	First 7K
PWP = PWP6K	First 6K
PWP = PWP5K	First 5K
PWP = PWP4K	First 4K
PWP = PWP3K	First 3K
PWP = PWP2K	First 2K
PWP = PWP1K	First 1K
PWP = OFF	Disable

Boot Flash Write Protect bit:

BWP = ON	Protection Enabled
BWP = OFF	Protection Disabled

Code Protect:

CP = ON	Protection Enabled
CP = OFF	Protection Disabled

**Microchip Technology Inc.**[Microchip Web Site](#)

Voice: (480) 792-7200

Fax: (480) 792-7277

[Microchip Technical Support](#)

Help Updated: 10/17/11 09:17:25